



GE  
Lighting

## 49490 - GE Quartz Metal Halide T12 - Stage & Studio

CSR1200/2/SE

### GENERAL CHARACTERISTICS

Base Type	Pin/Plug-In
Mercury-Picogram per mean lm hr	965.9
Rated Life Hours-nominal	800 h
Mercury Content EMEA ONLY	85
Primary Application	Stage & Studio
Product Technology	High Intensity Discharge
Base	G22/30X53
Bulb Shape	T12

### PHOTOMETRIC CHARACTERISTICS

Effective Arc Length	10 in
Nominal Lumens per Watt	92 lm
Initial Lumens-nominal	110000 lm
Color Rendering Index-CRI	75
Color Temperature	7200 K

### PRODUCT INFORMATION

Product Code	49490
Description	CSR1200/2/SE
Alternative Unit Of Measure	EACH
Standard Package Quantity	6
Ean UPC	043168494908
Standard Package GTIN	00043168494908
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	6
Sales Unit	Each
UCC	043168494908
Alternative Unit Of Measure	CASE

### DIMENSIONS

Diameter	1.5 in
Light Center Length Millimeter	3.35 in

### ELECTRICAL CHARACTERISTICS

Burn Position	Universal burning position
Rated power (Watts)	1200 W

### CAUTIONS & WARNINGS

**WARNING:** This lamp can cause serious skin burn and eye inflammation from shortwave ultraviolet radiation if outer envelope of the lamp is broken or punctured, and the arc tube continues to operate. Do not use where people will remain for more than a few minutes unless adequate shielding or other safety precautions are used. Certain types of lamps that will automatically extinguish when the outer envelope is broken or punctured are commercially available. Visit the FDA website for more information: <http://www.fda.gov/cdrh/radhealth/products/urburns.html>

#### Caution

Cut hazard--possible jagged glass

Wear gloves when handling

Wear gloves when handling

#### Risk of Burn

Allow lamp to cool before handling

Do not turn on lamp until fully installed

Allow lamp to cool before handling.

Do not turn on lamp until fully installed.

Allow lamp/fixture to cool before handling.

Turn power off before installing lamp.

Lamp may shatter and cause injury if broken

Dispose of lamp in a closed container

Do not use excessive force when installing lamp

Do not use lamp if outer glass is scratched or broken

Dispose of lamp in a closed container.

Do not use lamp if outer glass is scratched or broken.

Do not use excessive force when installing lamp.

Do not use lamp if outer glass is scratched or broken.

Dispose of lamp in a closed container.

#### Warning

A damaged lamp emits UV radiation which may cause eye/skin injury

Turn power off if glass bulb is broken. Remove and dispose of lamp.

#### Risk of Electric Shock

Turn power off before inspection

installation or removal.

Do not use where directly exposed to water or outdoors without an enclosed fixture.

Do not use where directly exposed to water or outdoors without an enclosed fixture

Turn power off before inspection

installation or removal

#### Risk of Fire

Keep combustible materials away from lamp.

Use in enclosed fixture rated for this product.

Keep combustible materials away from lamp.

Use in enclosed fixture rated for this product.

Keep combustible materials away from lamp

Use in enclosed fixture rated for this product

#### Unexpected lamp rupture may cause injury, fire, or property damage

Avoid direct water/liquid contact.

Use in enclosed fixture rated for this product.

Do not use lamp if outer glass is scratched or broken.

Do not exceed 110% of rated voltage.

Do not exceed rated voltage.

Do not store flammable materials near/below S-rated lamp in open fixture

Do not use lamp if outer glass is scratched or broken.

Do not touch glass with bare hands.

Operate lamp only in specified position.

Use in enclosed fixture rated for this product.

Do not turn on lamp until fully installed.

Do not turn on lamp until fully installed

Do not use lamp if outer glass is scratched or broken

Do not use beyond rated life.

Use only properly rated ballast.

#### Lamp emits UV radiation which may cause eye/skin injury. RG-3

Avoid exposure of eyes and skin to unshielded lamp.

#### Lamp emits UV radiation which may cause eye/skin injury. RG-3

Avoid exposure of eyes and skin to unshielded lamp

#### NOTES

Enclosed fixture only, per UL Standard 1572. In accordance to Federal Regulations 21 CFR 1040.30 the following notice applies: WARNING: This lamp can cause serious skin burn and eye inflammation from shortwave ultraviolet radiation if the outer envelope of the lamp is broken or punctured, and the arc tube continues to operate. Do not use where people will remain more than a few minutes unless adequate shielding or other safety precautions are used. Certain types of lamp that will automatically extinguish when the outer envelope is broken or punctured are commercially available.